



Features:

- Fuse reducers install on fuses and permit smaller size fuses to be used in larger amp size switches and blocks.
- Reducers will fit into any panel or switch including the dead-front type.
- Strong contact is maintained both mechanically and electrically.
- UL Listed.
- There are no reducers to go from 250V to 600V.
- There are no reducers for switching from one fuse class to another.
- There are no reducers for Class T or Class L fuses.

Fuses Reducers for Class H, J, K, & R Fuses

Agency Approvals: UL Listed,
Guide #IZZR, File #E12853
CSA Certified,
Class 6225-01, File 47235

Fuse Reducers for Class J Dimension Fuses- JDL, JFL, & CJ

| Fuse Size | Desired Size | Catalog No. (Pairs) | |
|-----------|--------------|---------------------|--|
| | | Reducer No. | |
| 30A | 60A | **J-63 | |
| 30A | 100A | **J-13 | |
| 60A | 100A | **J-16 | |
| 60A | 200A | **J-26 | |
| 100A | †200A | **J-21 | |
| 100A | †400A | **J-41 | |
| 200A | †400A | **J-42 | |
| 200A | 600A | **J-62 | |
| 400A | †600A | **J-64 | |

† Not for Bolt-on Applications.

** Product does not have UL or CSA certification.

**Fuse Reducers for Class R Dimension Fuses
ECNR, LENRK, NCLR; ECSR, LESRK, & SCLR**

| Fuse Size | Desired Size | Catalog No. (Pairs) | |
|-----------|--------------|---------------------|------------------|
| | | 250V Reducer No. | 600V Reducer No. |
| 30A | 60A | No. 263-R | No. 663-R |
| 30A | 100A | No. 213-R | No. 216-R |
| 60A | | No. 216-R | No. 616-R |
| 60A | 200A | No. 226-R | No. 626-R |
| 100A | | *No. 2621-R | |
| 100A | 400A | *No. 2641-R | |
| 200A | | *No. 242-R | *No. 642-R |
| 100A | | *No. 2661-R | |
| 200A | 600A | *No. 2662-R | |
| 400A | | **No. 2664-R | |

* Product does not have CSA certification.

**Single reducer only (pair not required)

Note: Carton quantity - 10 pair.

**Fuse Reducers for Class H & K Dimension Fuses
KON, ERN, PONC, CDNC; KOS, ERS, CDSC**

| Fuse Size | Desired Size | Catalog No. (Pairs) | |
|-----------|--------------|---------------------|------------------|
| | | 250V Reducer No. | 600V Reducer No. |
| 30A | 60A | No. 263 | No. 663 |
| 30A | 100A | No. 213 | No. 216 |
| 60A | 100A | No. 216 | No. 616 |
| 60A | 200A | No. 226 | No. 626 |
| 100A | 200A | No. 2621 | No. 2621 |
| 100A | 400A | *No. 2641 | *No. 2641 |
| 200A | 400A | No. 2642 | No. 2642 |
| 100A | 600A | *No. 2661 | *No. 2661 |
| 200A | 600A | *No. 2662 | *No. 2662 |
| 400A | 600A | *No. 2664 | *No. 2664 |

* Product does not have CSA certification.



Features:

- Fuse reducers install on fuses and permit smaller size fuses to be used in larger amp size switches and blocks.
- Reducers will fit into any panel or switch including the dead-front type.
- Strong contact is maintained both mechanically and electrically.
- UL Listed.
- There are no reducers to go from 250V to 600V.
- There are no reducers for switching from one fuse class to another.
- There are no reducers for Class T or Class L fuses.

Fuses Reducers for Class H, J, K, & R Fuses

Agency Approvals: UL Listed,
Guide #IZZR, File #E12853
CSA Certified,
Class 6225-01, File 47235

Fuse Reducers for Class J Dimension Fuses- JDL, JFL, & CJ

| Fuse Size | Desired Size | Catalog No. (Pairs) | |
|-----------|--------------|---------------------|--|
| | | Reducer No. | |
| 30A | 60A | **J-63 | |
| 30A | 100A | **J-13 | |
| 60A | 100A | **J-16 | |
| 60A | 200A | **J-26 | |
| 100A | †200A | **J-21 | |
| 100A | †400A | **J-41 | |
| 200A | †400A | **J-42 | |
| 200A | 600A | **J-62 | |
| 400A | †600A | **J-64 | |

† Not for Bolt-on Applications.

** Product does not have UL or CSA certification.

**Fuse Reducers for Class R Dimension Fuses
ECNR, LENRK, NCLR; ECSR, LESRK, & SCLR**

| Fuse Size | Desired Size | Catalog No. (Pairs) | |
|-----------|--------------|---------------------|------------------|
| | | 250V Reducer No. | 600V Reducer No. |
| 30A | 60A | No. 263-R | No. 663-R |
| 30A | 100A | No. 213-R | No. 216-R |
| 60A | | No. 216-R | No. 616-R |
| 60A | 200A | No. 226-R | No. 626-R |
| 100A | | *No. 2621-R | |
| 100A | 400A | *No. 2641-R | |
| 200A | | *No. 242-R | *No. 642-R |
| 100A | | *No. 2661-R | |
| 200A | 600A | *No. 2662-R | |
| 400A | | **No. 2664-R | |

* Product does not have CSA certification.

**Single reducer only (pair not required)

Note: Carton quantity - 10 pair.

**Fuse Reducers for Class H & K Dimension Fuses
KON, ERN, PONC, CDNC; KOS, ERS, CDSC**

| Fuse Size | Desired Size | Catalog No. (Pairs) | |
|-----------|--------------|---------------------|------------------|
| | | 250V Reducer No. | 600V Reducer No. |
| 30A | 60A | No. 263 | No. 663 |
| 30A | 100A | No. 213 | No. 216 |
| 60A | 100A | No. 216 | No. 616 |
| 60A | 200A | No. 226 | No. 626 |
| 100A | 200A | No. 2621 | No. 2621 |
| 100A | 400A | *No. 2641 | *No. 2641 |
| 200A | 400A | No. 2642 | No. 2642 |
| 100A | 600A | *No. 2661 | *No. 2661 |
| 200A | 600A | *No. 2662 | *No. 2662 |
| 400A | 600A | *No. 2664 | *No. 2664 |

* Product does not have CSA certification.